DESCRIPTION

The LM339DR-CN is quad independent precision voltage comparators capable of single or split supply operation. The LM339DR-CN is designed to permit a common mode range−to−ground level with single supply operation. Input offset voltage specifications as low as 3.0 mV make this device an excellent selection for many applications in consumer,automotive, andindustrial electronics.

The LM339DR-CN is available in a SOP14 package.


FEATURES

- Wide Supply Range:
  – Single Supply: 3.0V to 36V
  – Split Supply: ±1.5V to ±18V
- Low Input Bias Current: 25nA Typ
- Low Input Offset Current: ±5nA Typ

APPLICATIONS


- Industrial Equipment
- Automotive
- Power Monitoring
- Peak Detectors
- Logic Voltage Conversion

Pin Configuration



SOP14

Simplified Schematic(Each Comparator)



Absolute Maximum Ratings

Over operating free-air temperature range (unless otherwise noted)

PARAMETER		MIN	MAX	UNIT
Supply Voltage	Signal-supply		36	V
	Dual-supply		±18	V
Differential input voltage			±36	V
Input voltage range		-0.3	36	V
Output voltage			36	V
Input common mode voltage			V_{CC} - 1.5	V
Output Current			20	mA
Maximum Junction Temperature			+150	℃
Storage Temperature Range		-65	+150	℃
Lead Temperature(soldering, 10sec)			+260	℃

Recommended Operating Conditions

Over operating free-air temperature range (unless otherwise noted)

PARAMETER		MIN	TYP	MAX	UNIT
Supply Voltage, Vs=(V+) - (V-)	Signal-supply	3		32	V
	Dual-supply	±1.5		±16	V
Operating Temperature Range		-20	+25	+85	℃

Electrical Characteristics

(At T_A=+25℃, V_{CC}=5V, unless otherwise noted.)

PARAMETER	SYMBOL	CONDITIONS		MIN	TYP	MAX	UNIT
Input Offset Voltage	V_{IO}	T_A=25℃		-	±1	±5	mV
		-20℃≤ T_A ≤+85℃		-	-	±7	
Input Offset Current	I_{IO}	T_A=25℃		-	±5	±50	nA
		-20℃≤ T_A ≤+85℃		-	-	±150	
Input Bias Current	I_{IB}	T_A=25℃		-	25	250	nA
		-20℃≤ T_A ≤+85℃		-	-	400	
Input common mode voltage range	V_{ICR}	T_A=25℃		0	-	V_{CC} - 1.5	V
		-20℃≤ T_A ≤+85℃		0	-	V_{CC} - 2.0	
Supply Current	I_{CC}	R_L=∞, V_{CC}=5V		-	0.4	1.0	mA
		R_L=∞, V_{CC}=30V		-	0.45	2.5	
Voltage Gain	G_V	RL ≥ 15KΩ, V_{CC}=15V		50	200	-	V/mV
Response time	t_{RES}	V_{RL}=5V, R_L=5.1KΩ	TTL input with V_{REF}=1.4V	-	0.3	-	us
			Input overdrive=5mV, Input step=100mV	-	1.3	-	
Input differential voltage	V_{ID}	-		-0.3	-	V_{CC}	V

Low-level output current	I_{SINK}	IN- ≥ 1.0V, IN+ = 0V, V_O ≤ 1.5V	6	16	-	mA
Output saturation voltage	V_{SAT}	IN- ≥ 1.0V, IN+ = 0V, I_{SINK}≤4.0mA,	-	150	400	mV
		IN- ≥ 1.0V, IN+ = 0V, I_{SINK}≤4.0mA, -20℃≤ T_A ≤ +85℃	-	-	700	
Output Leakage Current	I_{OL}	IN+ ≥ 1.0V, IN- = 0V, V_O = 5V	-	0.1	-	uA
		IN+ ≥ 1.0V, IN- = 0V, V_O = 30V -20℃≤ T_A ≤ +85℃	-	-	1	

Typical Applications




Figure 1. Inverting Comparator with Hysteresis





Figure 2. Noninverting Comparator with Hysteresis



RS = Source Resistance
R1 ≃ RS

Logic	Device	V_{CC} (V)	R_L kΩ
CMOS	1/4 MC14001	+15	100
TTL	1/4 MC7400	+5.0	10

Figure 3. Driving Logic







Figure 4. Squarewave Oscillator


PACKAGE OUTLINE DIMENSIONS


SOP14











SYMBOL	MILLIMETER			SYMBOL	MILLIMETER		
	MIN	NOM	MAX		MIN	NOM	MAX
A	-	-	1.75	D	8.55	8.65	8.75
A1	0.10	-	0.225	E	5.80	6.00	6.20
A2	1.30	1.40	1.50	E1	3.80	3.90	4.00
A3	0.60	0.65	0.70	e	1.27BSC		
b	0.39	-	0.47	h	0.25	-	0.50
b1	0.38	0.41	0.44	L	0.50	-	0.80
c	0.20	-	0.24	L1	1.05REF		
c1	0.19	0.20	0.21	θ	0	-	8°

NOTICE

The information presented in this document is for reference only. Involving product optimization and productivity improvement, ChipNobo reserves the right to adjust product indicators and upgrade some technical parameters. ChipNobo is entitled to be exempted from liability for any delay or non-delivery of the information disclosure process that occurs.
本文件中提供的信息仅供参考。涉及产品优化和生产效率改善，ChipNobo 有权调整产品指标和部分技术参数的升级，所出现信息披露过程存在延后或者不能送达的情形，ChipNobo 有获免责权。

The product listed herein is designed to be used with residential and commercial equipment, and do not support sensitive items and specialized equipment in areas where sanctions do exist. ChipNobo Co., Ltd or anyone on its behalf, assumes no responsibility or liability for any damages resulting from improper use.
此处列出的产品旨在民用和商业设备上使用，不支持确有制裁地区的敏感项目和特殊设备，ChipNobo 有限公司或其代表，对因不当使用而造成的任何损害不承担任何责任。

For additional information, please visit our website http://www.chipnobo.com, or consult your nearest Chipnobo sales office for further assistance.
欲了解更多信息，请访问我们的网站 http://www.chipnobo.com，或咨询离您最近的 Chipnobo 销售办事处以获得进一步帮助。